

SPECIFICATION SHEET

ZEBRA® MAC OS® DRIVER SPECIFICATIONS FOR
ZXP SERIES 3 AND SERIES 1 CARD PRINTERS



Zebra® Mac OS Driver Specifications

ZXP SERIES 3™ AND ZXP SERIES 1™ CARD PRINTERS

The Zebra ZXP Series 3 Mac OS driver enables high-quality card printing in the Apple Mac OS X software environment. For customers who want to control their printer from a Mac computer, Zebra offers a fully functional Mac OS compatible print driver, which includes a core set of printer control functions that can be easily installed, tested and deployed for Mac based enterprise application deployments.

HIGHLIGHTED FEATURES

Printer USB Plug-In-Play (PNP)
Graphic User Interface (GUI)-based installer and uninstaller support
Zebra printer error handling support

MAC OS VERSION SUPPORT

Mac OS X 10.9 (Mavericks)
Mac OS X 10.10 (Yosemite)
Mac OS X 10.11 (El Capitan)

SUPPORTED FEATURES

PPD based GUI and custom Zebra ZXPS3 printer properties screen (device info, card setup, encoding, About Box)
Monochrome and Color single and dual side printing
Magnetic encoding from application and printer properties
Zebra printer properties page
YMCK front/K back ribbon combination supported
Card print orientation: portrait/landscape
Select single-side or dual-side print
K (black) panel
Full overlay varnish
Number of copies
Driver parameters print test card
Printer cleaning commands
Print Job log
Firmware download

SUPPORTED RIBBON MEDIA

	ZXP Series 3	ZXP Series 1
YMCKO	•	•
YMCKOK	•	
KdO	•	
KrO	•	
Monochrome	•	•
1/2 YMCKO	•	•

PRINTER FEATURES/OPTIONS NOT SUPPORTED IN ZXP S3 AND S1 MAC OS DRIVER

Smart card encoding (contact and contactless)
Network printer sharing and printer pooling
Advanced printer security features
Image control support
Black (K panel) print optimization (defined and undefined K panel printing)

DRIVER INSTALLATION FILE PATHS USED IN MAC OS PRINTER DRIVER

Mac Driver Installation Folder is /Library/Printers/Zebra_ZXPS3_S1_Card_Printer_Driver
CUPS Filter Installation Folder is in /usr/libexec/cups/filter (rastertozxp3)
PPD Installation Folder is /Library/Printers/PPDs/Contents/Resources
Log File Path /private/var/spool/cups/tmp/

VISIT THE ZXP SERIES 3 OR SERIES 1 DRIVER DOWNLOAD PAGE AT WWW.ZEBRA.COM
OR OUR GLOBAL CONTACT DIRECTORY AT WWW.ZEBRA.COM/CONTACT



NA and Corporate Headquarters
+1 800 423 0442
inquiry4@zebra.com

Asia-Pacific Headquarters
+65 6858 0722
contact.apac@zebra.com

EMEA Headquarters
zebra.com/locations
mseurope@zebra.com

Latin America Headquarters
+1 847 955 2283
la.contactme@zebra.com